

Lollar[®]

TACOMA, WA **PICKUPS**

Humbucker Wiring

4 Conductor Lead Wire
Single Humbucker - Coil Split Wiring
Tone Control

Use of a DPDT switch allows the two coils to be **split** leaving the **South coil (slug coil)** active.

Splitting the coils of a humbucker offers a true single coil tone by dropping one side of the humbucker from the signal path. This reintroduces 60 cycle hum back into the sound, but provides a brighter and more dynamic sound with lower output.

Four Conductor Lead Wire Color Coding

- **Black** - slug coil start - hot
- **White** - slug coil end - tap
- **Red** - screw coil end - tap
- **Green** - screw coil start - ground
- *Braided shield combined with green* - ground

