

Lollar[®]

TACOMA, WA **PICKUPS**

Humbucker Wiring

4 Conductor Lead Wire
Single Humbucker - Phase Wiring
Volume Control

Use of a DPDT switch allows the **phase** direction of the humbucker's output signal to **flip**, allowing for two pickups to be run in phase, or out of phase with each other.

Swapping the phase relationship between pickups from in phase to out of phase offers a unique thin, nasally, and lower output sound when the two pickups are combined. This will only be noticeable when the two pickups are combined.

Four Conductor Lead Wire Color Coding

- **Black** - slug coil start - hot
- **White** - slug coil end - tap
- **Red** - screw coil end - tap
- **Green** - screw coil start - ground
- *Braided shield combined with green* - ground

